

Brocade® Transceiver Support Matrix

				Gen 7				Gen 6				Gen 5					
	Description	Manufacturing Part Number	Brocade Ordering Part Number	Brocade X7	Brocade FC64-48	Brocade FC32-X7-48	Brocade G720	Brocade X6	Brocade FC32-64	Brocade FC32-48	Brocade G630	Brocade G620	Brocade G610	Brocade DCX 8510	Brocade 6520	Brocade 6510	Brocade 6505
64G FC SFP+	SWL	57-1000495-01	XBR-000462 (1-pack) XBR-000463 (8-pack)		● ¹		● ¹										
Gen 7 FC QSFP+	SWL	57-1000481-01	XBR-000420 (1-pack)	●													
8G FC SFP+	SWL	57-1000117-01	XBR-000163 (1-pack) XBR-000164 (8-pack)											●	●	●	●
	LWL - 10 km	57-1000027-02	XBR-000153 (1-pack) XBR-000172 (8-pack)											●	●	●	●
	ELWL - 25 km	57-0000080-01	XBR-000174 (1-pack)											●	●	●	●
10G FC SFP+	SWL	57-1000114-01	XBR-000218 (1-pack)							●	●	●		●	●	●	
	LWL - 10 km	57-1000115-01	XBR-000217 (1-pack)							●	●	●		●	●	●	
	SWL	57-1000492-01	XBR-000418 (1-pack)		●	●	●			●	●	●		●	●	●	
	LWL - 10 km	57-1000493-01	XBR-000417 (1-pack)		●	●	●			●	●	●		●	●	●	
16G FC SFP+	SWL	57-0000088-01	XBR-000192 (1-pack) XBR-000193 (8-pack)							●	●	●	●	●	●	●	●
	SWL	57-1000487-01	XBR-000492 (1-pack) XBR-000493 (8-pack)			●				●	●	●	●	●	●	●	●
	LWL - 10 km	57-0000089-01	XBR-000198 (1-pack) XBR-000199 (8-pack)							●	●	●	●	●	●	●	●
	LWL - 10 km	57-1000488-01	XBR-000498 (1-pack) XBR-000499 (8-pack)			●				●	●	●	●	●	●	●	●
	ELWL - 25 km	57-1000262-01	XBR-000258 (1-pack)							●	●	●	●	●	●	●	●
	ELWL - 25 km	57-1000489-01	XBR-000458 (1-pack)			●				●	●	●	●	●	●	●	●
4x16G FC QSFP+	SWL	57-1000294-01/-02	XBR-000245 (1-pack)					● ²	● ²		● ²	● ²		● ²			
	SWL	57-1000267-01	XBR-000232 (1-pack)											● ³			
	2 km	57-1000310-01	XBR-000255 (1-pack)					● ⁴						●			
32G FC SFP+	SWL	57-1000333-01	XBR-000212 (1-pack) XBR-000213 (8-pack)							●	●	●	●				
	SWL	57-1000485-01	XBR-000412 (1-pack) XBR-000413 (8-pack)		●	●	●			●	●	●	●				
	LWL - 10 km	57-1000332-01	XBR-000238 (1-pack) XBR-000239 (8-pack)							●	●	●	●				
	LWL - 10 km	57-1000486-01	XBR-000438 (1-pack) XBR-000439 (8-pack)		●	●	●			●	●	●	●				
	ELWL - 25 km	57-1000355-01	XBR-000278 (1-pack)							●	●	●	●				
	ELWL - 25 km	57-1000494-01	XBR-000478 (1-pack)		● ¹	● ¹	● ¹			●	●	●	●				
4x32G FC QSFP+	SWL	57-1000351-01	XBR-000275 (1-pack)					●	●		●	●					
	SWL	57-1000490-01	XBR-000475 (1-pack)	●				●	●		●	●					
	2 km	57-1000480-01	XBR-000285 (1-pack)	● ¹				● ⁵	● ⁵		●	●					
Ethernet QSFP+	40GBASE-SR4 or 4x10GbE	57-1000129-01	XBR-40G-SR4-INT-0286							● ⁶							
	40GbE BiDi	57-1000339-01	XBR-40G-SR-BIDI-0287							● ⁶							
	100GBASE-SR4 or 4x25GbE	57-1000326-01	XBR-100G-SR4-0288							● ⁶							

¹ Minimum FOS version is 9.0.1a.

² FC-compliant QSFPs are supported on ICLs (DCX 8510 and X6) and the FC16-64, FC32-64, G620, and G630.

³ The last customer ship date was January 2017.

⁴ ICL only. Not supported on the FC32-64.

⁵ The 4x32G FC 2-km QSFP on X6 ICL ports requires FOS 8.1.0b or higher.

⁶ Supported on the FC32-64 for FCoE connectivity only.

Brocade® Transceiver Support Matrix

				Gen 4		Extension		
	Description	Manufacturing Part Number	Brocade Ordering Part Number	Brocade 300	Brocade 7800	Brocade SX6	Brocade 7840	Brocade 7810
4G FC SFP+	SWL	57-1000013-01	XBR-000139 (1-pack) XBR-000141 (8-pack) XBR-000158 (128-pack)	●	● ⁷			
	LWL - 4 km	57-1000014-01	XBR-000142 (1-pack) XBR-000143 (8-pack)	●	● ⁷			
	LWL - 10 km	57-1000015-01	XBR-000144 (1-pack) XBR-000157 (8-pack)	●	● ⁷			
	ELWL - 30 km	57-1000020-01	XBR-000146 (1-pack)	●	● ⁷			
8G FC SFP+	SWL	57-1000012-01	XBR-000147 (1-pack) XBR-000148 (8-pack) XBR-000159 (128-pack)	(EOL)	(EOL)			
		57-1000117-01	XBR-000163 (1-pack) XBR-000164 (8-pack)	●	●		●	
	LWL - 10 km	57-1000027-02	XBR-000153 (1-pack) XBR-000172 (8-pack)	●	●		●	
	ELWL - 25 km	57-0000080-01	XBR-000174 (1-pack)	●	●		●	
10G FC SFP+	SWL	57-1000114-01	XBR-000218 (1-pack)			●		
	LWL - 10 km	57-1000115-01	XBR-000217 (1-pack)			●		
	SWL	57-1000492-01	XBR-000418 (1-pack)			● ⁸		
	LWL - 10 km	57-1000493-01	XBR-000417 (1-pack)			● ⁸		
16G FC SFP+	SWL	57-0000088-01	XBR-000192 (1-pack) XBR-000193 (8-pack)			●	●	●
	SWL	57-1000487-01	XBR-000492 (1-pack) XBR-000493 (8-pack)			● ⁸	●	● ⁸
	LWL - 10 km	57-0000089-01	XBR-000198 (1-pack) XBR-000199 (8-pack)			●	●	●
	LWL - 10 km	57-1000488-01	XBR-000498 (1-pack) XBR-000499 (8-pack)			● ⁸	●	● ⁸
	ELWL - 25 km	57-1000262-01	XBR-000258 (1-pack)			●	●	
	ELWL - 25 km	57-1000489-01	XBR-000458 (1-pack)			● ⁸	●	
32G FC SFP+	SWL	57-1000333-01	XBR-000212 (1-pack) XBR-000213 (8-pack)			●		●
	SWL	57-1000485-01	XBR-000412 (1-pack) XBR-000413 (8-pack)			● ⁸		● ⁸
	LWL - 10 km	57-1000332-01	XBR-000238 (1-pack) XBR-000239 (8-pack)			●		●
	LWL - 10 km	57-1000486-01	XBR-000438 (1-pack) XBR-000439 (8-pack)			● ⁸		● ⁸
	ELWL - 25 km	57-1000335-01	XBR-000278 (1-pack)			●		
Ethernet QSFP+	40GBASE-SR4	57-1000128-01	XBR-40G-SR4-INT-0286			●	●	
	40GbE BiDi	57-1000339-01	XBR-40G-SR-BIDI-0287			● ⁸		
	40GBASE-LR4 - 10 km	57-1000263-01	40G-QSFP-LR4			●	●	
	40GBASE-ER4 - 40 km	57-1000327-01	40G-QSFP-ER4			●		
1GbE SFP+ (Copper)	1GbE Copper	57-1000042-01	XBR-000190 (1-pack)		●	●	●	●
1GbE SFP+	1000 BASE-SX	33210-100	E1MG-SX-OM (1-pack) E1MG-SX-OM-8 (8-pack)			●	●	●
	1000 BASE-LX	33211-100	E1MG-LX-OM (1-pack) E1MG-LX-OM-8 (8-pack)			●	●	●
10GbE SFP+	SR	57-0000075-01	XBR-000180 (1-pack) XBR-000181 (8-pack)			●	●	●
	LR	57-0000076-01	XBR-000182 (1-pack) XBR-000183 (8-pack)			●	●	●
	USR	57-1000130-01	10G-SFPP-USR (1-pack) 10G-SFPP-USR-8 (8-pack)			●	●	●

⁷ Also qualified at 1GbE speed.

⁸ For the SX6 and 7810 platforms, secure optics require FOS 8.2.1.e or 8.2.2.c or higher. For all other Brocade platforms, there is no FOS requirement for secure optics.

⁹ Requires FOS 8.2.1b.

Broadcom, the pulse logo, Connecting everything, Brocade, the stylized B logo, and DCX are among the trademarks of Broadcom. The term "Broadcom" refers to Broadcom Inc. and/or its subsidiaries.

Copyright © 2018-2021 Broadcom Inc. All Rights Reserved.

For product information, please visit broadcom.com. GA-MX-460-14 March 10, 2021